



FLEXISCAN

110° PIR SECURITY SENSOR



- 240V
- Detection Scan: 110°
- Detection Range: 18m
- Time on: 5s~10min
- Lux Setting
- Max Load: 2400W
- IP66

LED Compatible
 Passive Infra-red technology
 Multi-segmented optical lens for better detection
 3-Wire design for greater reliability
 IP66 Weather-resistant Rated
 Wall or ceiling installation
 Heavy duty switching circuitry, suitable for large loads
 Easy to mount
 Max Load: 2400W Incandescent
 1200W Inductive
 600W LED
 Power consumption: 0.7W
 Operating Temp: -5 to 45 degrees Celsius
 5-Year Warranty

Code:	18562/..
06 BLACK	9 312641 198468 >
09 BEIGE	9 312641 185628 >



UNI-SCAN

180° PIR SECURITY SENSOR



- 240V
- Detection Scan: 180°
- Detection Range: 12m
- Time on: 10s~4min
- Lux Setting
- Manual Override
- Max Load: 1000W
- IP44

Passive Infra-red technology
 Multi-segmented lens for better detection
 3-Wire design for greater reliability
 IP44 Weather-resistant Rated
 Max Load: 1000W Incandescent
 300W Inductive
 150W LED
 Operating Temp: -5 to 45 degrees Celsius
 2-Year Warranty

Code:	18060/..
05 WHITE	9 312641 180616 >
06 BLACK	9 312641 180609 >